

	<b>4632</b>		<b>3632</b>	
	LF	M/HF	LF	M/HF
gain	+2dB	-6dB	+1dB	-4dB
delay	0.292ms	0	1.458ms	0
polarity	(-)	(+)	(+)	(+)
h.p.f.	LR12,25hz	Butt18, 250hz	LR12, 25hz	LR24, 353hz
l.p.f.	LR24, 250hz	n/a		LR24, 450hz
eq	125hz, -3dB, 0.45oct	n/a	176hz, -5dB, 0.35oct	5.92k, -2dB, 0.4oct
eq			341hz, +3dB, 0.35oct	

**LF:**

1.458 ms delay

Linkwitz-Rielly 12dB/oct. High pass filter at 25hz (protection filter)

Linkwitz-Rielly 24dB/oct. Low pass filter at 353hz (crossover filter)

**HF:**

Linkwitz-Rielly 24dB/oct. Low pass filter at 450hz (crossover filter)

	<b>4632T</b>	<b>3632T</b>
Master Shape/Slope:	24dB / Butterworth	24dB / L.R.
MF HPF	300, 18dB/oct	450, 24dB/oct
MF LPF	1k10, 24dB/oct	1k46, 18dB/oct
HF HPF	1k51, 24dB/oct	1k31, 18dB/oct
MF delay	0.124 ms	0.124 ms
HF delay	0.0 ms	0.0 ms
MF EQ 1	1k23, 0.20 oct, +6dB	707, 0.55 oct, 3dB
MF EQ 2	500, 080 OCT, -4.5dB	2k54, 0.5 oct, -9dB
HF EQ 1	3k03, 0.30 oct, -3dB	3k03, 0.65 oct, -3dB
HF EQ 2	10k9, 6dB/oct, +14dB	5k09, 12dB/oct, +7.5dB
MF Level	0.0dB	0.0dB
HF Level	-9.4dB	-5.4dB
Limiters	out	out
Polarity	all(+)’ve	all(+)’ve